

**SHURE**

# SLXD5+ SINGLE-CHANNEL PORTABLE DIGITAL WIRELESS RECEIVER

## SPECIFICATIONS

(SUBJECT TO CHANGE)

<b>Dimensions (H • W • D)</b>	4.21 • 2.68 • 1.0 in (107 • 68 • 25.3 mm)
-------------------------------	--

<b>Weight</b>	1.8 lb (182 g)
---------------	----------------

<b>Housing</b>	Aluminum
----------------	----------

<b>Power Requirements</b>	Battery: Rechargeable Li-Ion or 1.5 V AA batteries Power Supply: SBC-DC-903 Battery Eliminator, or 5 VDC via USB-C
---------------------------	---

### RF INPUT

<b>Spurious Rejection</b>	>75 dB Typical
---------------------------	-------------------

<b>Impedance</b>	50 $\Omega$
------------------	-------------

<b>Phantom Power Protection</b>	Yes
---------------------------------	-----

<b>Antenna Type</b>	1/4 Wave Whip
---------------------	---------------

### AUDIO OUTPUT

<b>Audio Frequency Response</b>	20 Hz – 20 kHz (+1, -3 dB)
---------------------------------	-------------------------------

<b>Connector Type</b>	1/8" (3.5 mm), x2
-----------------------	-------------------

<b>Configuration</b>	Balanced (Mono): Tip=audio +, Ring=audio -, Sleeve=ground Dual Mono: Tip = left, Ring = Right, Sleeve = Ground
----------------------	---

<b>Impedance (Camera)</b>	Balanced (Mono) Line: 450 $\Omega$ Balanced (Mono) Mic: 340 $\Omega$ Dual Mono Line: 400 $\Omega$ Dual Mono Mic: 200 $\Omega$
---------------------------	--

<b>Full Scale Output</b>	Camera (Balanced Line): 15 dBV Headphone: 13 mW @ 64 $\Omega$ Load
--------------------------	---

## OVERVIEW

The SLXD5+ single channel portable wireless receiver is at home on top of your camera or in an audio bag providing efficient long-range UHF transmission and easy-to-use setup features to deliver wireless excellence, wherever required. Wide-tuning SLXD+ transmitters and receivers stay in sync courtesy of a dedicated ShowLink® Ease control link. Manage interference, scan for new channels and update for clear transmission automatically. Also monitor and configure via a paired mobile device.

## FEATURES

- Single channel, portable digital wireless receiver for on-camera cold shoe mounting and audio bag use
- Transparent 24-bit digital audio quality with >118 dB dynamic range
- Rock solid RF with 138 MHz wide-tuning range for greater geographical coverage:
  - > Up to 11 simultaneous systems in 6 MHz TV bands
  - > Up to 14 simultaneous systems in 8 MHz TV bands
- Dual 1/8" outputs including a headphone monitor out and switchable line/mic output
- Automatic Setup - once linked, SLX-D+ receivers and transmitters stay connected, despite any RF interference
- With ShowLink® Ease, transmitter parameters can be adjusted remotely over the air from the linked receiver, including:
  - > Changing the transmitter frequency once open frequency is identified
  - > Adjust transmitter gain
  - > Automatically find and deploy new frequency to both receiver and transmitter upon interference
  - > Lock and unlock transmitter controls
  - > Transmitter firmware updates
- Use Multi-Mic Mode to scan and sync over IR multiple clean frequencies, and monitor multiple sources from a single receiver with user-configurable front-panel controls
- Monitor RF status and control receiver and transmitter parameters with Wireless Workbench desktop software, or remotely with the WWB Mobile app over Wi-Fi or Bluetooth
- Patented Shure Digital Feedback Reducer software is embedded in every SLX-D+ receiver, to automatically reduce unwanted audio feedback, should it ever occur.
- Each SLX-D+ component and system ships with AES-256 Encryption installed, for complete and secure peace of mind
- Up to 5.5 hours of use from either 2 AA batteries (included) or optional Shure SB903 Li-ion rechargeable batteries and charging accessories



**SLXD5+**  
Single-Channel Portable  
Digital Wireless Receiver