

## TECHNICAL SPECIFICATIONS



### iLIVE 2 HEADSET

**iLive 2 headset antenna diversity wireless microphone system with 32 selectable channels with automatic channel targeting and synchronization.**

The microphone signal receiver, body pack transmitter with head-worn, body color condenser microphone and jack/jack cable are included in each set. The system is used on the stage and in the conference rooms.

	<b>iLive 2 receiver</b>
Power supply	12-15 V DC, 1.25 A
Output	Balanced XLR , unbalanced 6,3 mm TS JACK
Receiver way	Two frequency conversion super-heterodynes
Intermediate frequency	10,7 MHz
Antenna	BNC
T.H.D	< 0,7 %
Sensitivity	6 dB $\mu$ V
Image rejection	36 dB
Max. audio output	0 dB
Dimensions (H x W x D)	45 mm x 210 mm x 206 mm
Weight	1.3 kg
Material	Steel enclosure, aluminum front panel
	<b>iLIVE 2 body pack transmitter</b>
Carrier frequency range	606 MHz - 621 MHz
Modulation	FM
Channels	32
Audio frequency response	45 Hz - 18 kHz
S/N ratio	> 105 dB
Antenna	1/4 wave antenna
Transmitter's power	15 mW
Working range	60 m (Note: actual range depends on RF signal absorption, reflection, and interference)
Inputs	4 pin mini XLR connector
Dimensions (H x W x D)	110 mm x 64 mm x 25 mm
Weight	76 g
Material	Plastic
	<b>iLIVE 2 HM microphone</b>
Capsule type	Condenser
Impedance	200 $\Omega$
Sensitivity	- 47 dB
Frequency	45 Hz - 18 kHz
Connectors	4 pin mini XLR connector
Phantom power voltage	5V DC
Cable length	1 m
Weight	15 g
Colour	Skin (RAL 1014)
Accessories	Windscreen