grandMA3 4Port Node DIN-Rail

Art.-No. 4011702

The grandMA3 4Port Node DIN-Rail is the installation allrounder within MA Lighting´s range of Nodes. It ensures optimal DMX distribution in any theatre, television or house of worship installation. Do you have a venue where you need DMX lines in many different places? Then the grandMA3 4Port Node DIN-Rail is the ideal solution.

The grandMA3 4Port Node DIN-Rail synchronously outputs four DMX universes from any grandMA3 session and can be entirely powered by PoE (Power over Ethernet). It is perfectly suited for any kind of fixed installation due to its modern and easy-to-mount DIN rail housing design.

To ensure optimal performance, the Node is equipped with a high-performance processor and a 1 Gb/s Ethernet connection, guaranteeing reliable and stable Ethernet to DMX (and vice versa) conversion. It is remotely configurable from any grandMA3 console or onPC station within the network. The Node is capable of handling MA-Net3, MA-Net2, sACN and Art-Net data and is fully RDM compliant. A 3.9" color display on the front face allows for simple configuration and a quick status overview.

Scope of delivery

Art.-No.	Article	Quantity
4025837	MA Quick Manual for grandMA3 Nodes DIN-Rail	1

1x connector for power supply (MC 1,5/ 3-ST1-5,08), Art.No. 4022468
4x connector for DMX/MIDI/LTC (FK-MC 0,5/ 3-ST-2,5), Art.No. 4022469

Technical Specifications

Parameters	none
Parameters Mode2	none
Operating voltage/ Supply voltage	AC 100 - 240 V; 50/60 Hz PoE (IEEE 802.3af; 48 V DC/max. 12 W)
Power	max. 15 VA
Operating Temperature	-10 °C up to 50 °C / 14 °F up to 122 °F
Dimensions	150 x 50 x 90 mm / 6 x 2 x 4 in (width x depth x height)
Net weight	1 kg / 3 lbs
Connectors	1 x Power (3pin PCB connector) 1 x Ethernet/RJ45 4 x DMX512-A Out (3pin PCB connector) 1 x USB 2.0 (type A)

Article

Art.-No.	Article
4011702	grandMA3 4Port Node DIN-Rail

Accessories

Art.-No.	Article
4021730	Adapter cable set for grandMA3 4Port Node DIN-Rail, DMX via XLR 5pin, (4x cable DMX/XLR5 (length 0.5m), 1x cable RJ45, 1x built-in socket etherCON/ RJ45 to RJ45)
4021733	Adapter cable set for grandMA3 4Port Node DIN-Rail, DMX via RJ45, (4x cable DMX/RJ45 (length 0.5m), 1x cable RJ45, 1x built-in socket etherCON/ RJ45 to RJ45)

More product pictures